

INFORMATION UPDATE


** Please direct this publication to the department or individual responsible **

COINCO BP4SX With NEXGEN \$10

Subject: INSTALLING A COINCO BP4SX IN A CENTURY CHANGER

Products Affected: C2, C6, C8, C10, C6RL, C10RL

Coinco® BP4SX acceptors that have been built or upgraded to accept the new 2004 Series “NexGen” \$10 bills require different setup programming than for past Coinco acceptors, when installed in a Century Changer. Models which can accept this new bill are marked as shown below - “\$10” is printed in the Coupon Accept box. If you have one of these bill acceptors, program the Century Computer as shown below. (Programming instructions for the Coinco unit are included with the bill acceptor.)



Coin Acceptor Settings -- **No Change**
Meter Settings -- **No Change**

Coin Level Settings -- **No Change**
Payout Settings -- **No Change**

ba 4 (for MDB)
b1 1 (\$1 bill on)
b2 1 (new \$5 bill on)
b3 1 (new \$10 bill on)
b4 1 (NexGen \$10 bill on)
b5 Must be set to 0
b6 (Nexgen \$20 on)
b7 (new \$20 bill on)

1b04 (4 quarters = \$1)
2b20 (20 quarters = \$5)
3b40 (40 quarters = \$10)
4b40 (40 quarters = \$10)

6b80 (80 quarters = \$20)
7b80 (80 quarters = \$20)

Important Note: The \$1 bill is the **only** small portrait bill that can be accepted.



id 260 February 2006

Rowe International Corp. * 1500 Union SE * Grand Rapids MI 49507-1884

Gordy Anderson
Director
Technical Services